

Power Supply Specs

| Model # | Input Voltage | Input current | Input power | # Outlets | Output power | Output energy |
|---------------|---------------|---|-------------|-----------|--------------|---------------|
| QUICKSTROBE | 10 to 30 VDC | 1.2 amps @ 12.8VDC, .6 amps @ 25.6VDC | 15.4 watts | 1 | 12.4 watts | 10.64 Joules |
| QUADPAK202 | 10 to 30 VDC | 1.8 amps @ 12.8VDC, 1 amp @ 25.6VDC | 24 watts | 2 | 20 watts | 17.46 Joules |
| EPSX402 | 10 to 30 VDC | 3.75 amps @ 12.8VDC, 2 amps @ 25.6VDC | 50 watts | 2 | 40 watts | 34 Joules |
| EPSX404 | 10 to 30 VDC | 3.75 amps @ 12.8VDC, 2 amps @ 25.6VDC | 50 watts | 4 | 40 watts | 34 Joules |
| EPSX406 | 10 to 30 VDC | 3.75 amps @ 12.8VDC, 2 amps @ 25.6VDC | 50 watts | 6 | 40 watts | 34 Joules |
| MICROPAK404X | 10 to 30 VDC | 3.75 amps @ 12.8VDC, 2 amps @ 25.6VDC | 50 watts | 4 | 40 watts | 34 Joules |
| MICROPAK504X | 10 to 30 VDC | 4.5 amps @ 12.8VDC, 2.2 amps @ 25.6VDC | 57 watts | 4 | 50 watts | 40 Joules |
| XPAK604X | 10 to 30 VDC | 5.5 amps @ 12.8VDC, 2.6 amps @ 25.6VDC | 70.4 watts | 4 | 60 watts | 51.5 Joules |
| XPAK604PE | 10 to 30 VDC | 5.5 amps @ 12.8VDC, 2.6 amps @ 25.6VDC | 70.4 watts | 4 | 60 watts | 51.5 Joules |
| XPAK804 | 10 to 30 VDC | 7.75 amps @ 12.8VDC, 4.0 amps @ 25.6VDC | 100 watts | 4 | 80 watts | 72 Joules |
| XPAK904 | 10 to 30 VDC | 8.5 amps @ 12.8VDC, 4.2 amps @ 25.6VDC | 110 watts | 4 | 90 watts | 80 Joules |
| SUPERPAK606X | 10 to 30 VDC | 5.5 amps @ 12.8VDC, 2.6 amps @ 25.6VDC | 70.4 watts | 6 | 60 watts | 51.5 Joules |
| SUPERPAK806 | 10 to 30 VDC | 7.75 amps @ 12.8VDC, 4.0 amps @ 25.6VDC | 100 watts | 6 | 80 watts | 66 Joules |
| SUPERPAK906 | 10 to 30 VDC | 8.3 amps @ 12.8VDC, 4.15 amps @ 25.6VDC | 110 watts | 6 | 90 watts | 74.4 Joules |
| DOUBLEPAK1208 | 10 to 30 VDC | 11 amps @ 12.8VDC, 5.2 amps @ 25.6VDC | 150 watts | 8 | 120 watts | 103 Joules |
| ULTRAPAK1858 | 10 to 16 VDC | 18 amps @ 12.8VDC | 230 watts | 8 | 185 watts | 147.32 Joules |
| ULTRAPAK18510 | 10 to 16 VDC | 18 amps @ 12.8VDC | 230 watts | 10 | 185 watts | 147.32 Joules |
| ULTRAPAK18512 | 10 to 16 VDC | 18 amps @ 12.8VDC | 230 watts | 12 | 185 watts | 147.32 Joules |
| RPM460 | 10 to 30 VDC | 5.5 amps @ 12.8VDC, 2.6 amps @ 25.6VDC | 70.4 watts | 4 | 60 watts | 51.5 Joules |
| RPM480 | 10 to 30 VDC | 7.75 amps @ 12.8VDC, 3.5 amps @ 25.6VDC | 100 watts | 4 | 80 watts | 72 Joules |
| RPM490 | 10 to 30 VDC | 8.5 amps @ 12.8VDC, 4.0 amps @ 25.6VDC | 110 watts | 4 | 90 watts | 80 Joules |
| RPM660 | 10 to 30 VDC | 5.5 amps @ 12.8VDC, 2.6 amps @ 25.6VDC | 75 watts | 6 | 60 watts | 51.5 Joules |
| RPM680 | 10 to 30 VDC | 7.75 amps @ 12.8VDC, 3.5 amps @ 25.6VDC | 100 watts | 6 | 80 watts | 72 Joules |
| RPM690 | 10 to 30 VDC | 8.5 amps @ 12.8VDC, 4.0 amps @ 25.6VDC | 110 watts | 6 | 90 watts | 80 Joules |
| REG480 | 10 to 16 VDC | 7.75 amps @ 12.8VDC | 100 watts | 4 | 80 watts | 68 Joules |
| REG8160 | 10 to 16 VDC | 16 amps @ 12.8VDC | 200 watts | 8 | 160 watts | 136 Joules |
| BUS8PS | 10 to 16 VDC | 12.5 amps @ 13VDC | 160 watts | 8 | 135 watts | 30 Joules |
| HPS480 | 10 to 30 VDC | 7.75 amps @ 12.8VDC, 4 amps @ 25.6VDC | 100 watts | 4 | 80 watts | 82 Joules |
| LEDFLASHER | 12.8 VDC | 10 Amps max per output | N/A | 2 | N/A | N/A |
| INTELLIPAK2 | 10 to 16 VDC | 0.5A Max | 6.5 watts | 2 | N/A | N/A |
| INTELLIPAK4 | 10 to 16 VDC | 1.25A Max | 16.25 watts | 4 | N/A | N/A |

Self-Contained Warning Heads Specs

| Model # | Input Voltage | Input current | Input power | Output power | Output energy |
|-------------|---------------|--------------------------------------|-------------|--------------------------------|---------------------------------------|
| MICRODASH | 10 to 16 VDC | 2 Amps @ 12.8V | 25 Watts | 20 Watts | 17 Joules |
| MDASHCPE | 10 to 16 VDC | 1.35 Amps @ 12.8V | 17.3 Watts | 15 Watts (High) 10 Watts (Low) | 14.65 Joules (High) 9.74 Joules (Low) |
| WIC3SC | 10 to 30 VDC | 1.0 Amps @ 12.8V, 0.5Amps @ 25.6V | 13 Watts | 10.6 Watts | 9.2 Joules |
| EZSTROBE | 10 to 30 VDC | 1.25 Amps @ 12.8V, 0.65 Amps @ 25.6V | 16 Watts | 12 Watts | 10.34 Joules |
| LEDMICROBAR | 12.8 VDC | 2.0 Amps Max | 25.6 Watts | N/A | 116 Lumens/ head |
| MICROBAR360 | 10 to 30 VDC | 3.0 Amps @ 12.8V, 1.4 Amps @ 25.6V | 40 Watts | 30 Watts | 27.2 Joules |